# HYBRID SOLID STATE RELAY

## **PROTON RAD HARD 100K + ® TECHNOLOGY**



# Series Features

#### Rad Hard: TID > 100kRad(Si)

- 2:1 margin: Operates beyond 200kRad TID
- No SEE:LET > 82MeV\*cm<sup>2</sup>/mg
- Proton Resistant: No optocouplers used
- User programmable rise time to customize inrush current response
- Dual logic level command input, 3.3 or 5 volts
- Large internal FET heatsink integrates thermal turn-on pulse for low stress operation
- 100K+<sup>™</sup> patented design for reliable operation in space environments

#### Specifications \*3647

#### SPST NO, Single Channel

Switch Input Voltage Range:

Static Characteristics - Table 1

Dynamic Response - Table 2 Radiation Life - Table 3

Isolation: 500 VDC

All active pins to case

Command inputs to switch

Bias supply to switch

Bias Input Voltage: 5 VDC (4.6 VDC - 5.4 VDC)

Bias Input Current 30 mA typical

3.3 VDC bias input optional

- Command Buffer input current 1 mA typical at 5 VDC
- Command Buffer trip point 1.5 VDC (OFF 1V max, ON 2V min)
- Power dissipation: 4 W max continuos steady state
- Case Temperature Range
  - Storage: -65°C to 150°C
  - Operating: -55°C to 85°C (R or S grades) Operating: -55°C to 125°C (RE or SE grades)

#### WEIGHT: 45 grams typical



#### Max. Max. Steady

Model Number	Application Bus Voltage	Recommended Input Voltage	Rated Input Voltage	Peak Current	Steady State Current	On Resistance	at max rated	at Application Bus Voltage
	Vdc	Vdc	Vdc	A	Α	Ohms	μA	μA
33647	120	158	250	7	1.5	0.75	20	10
93647	100	120	250	7	1.5	0.75	20	10
83647	70	120	250	7	1.5	0.75	20	10
73647	50	75	150	15	4	0.15	200	100
53647	28	75	150	15	4	0.15	200	100

•Application Bus Voltage in the commonly available satellite bus voltage ranges. These ratings harmonize with the input voltage ranges for MDI 5000, 7000, 8000 and 9000 series converters. Model 33647 designed for International Space Station and Orion MPCV applications.

•Maximum Recommended Input Voltage is the maximum factory recommendation considering single event radiation effects •Maximum Rated Input Voltage is the maximum Vds rating of the FET switch

- Peak Current Maximum transient current
- •Steady State Current Maximum continuous steady state current

TABLE 1: SSR Ratings and Static Characteristics

•On Resistance - Typicals in ohms, 25C. Increases linearly to 2X at 125C.

- •Leakage Current at Max Rated Input Voltage OFF State Typical values
- •Leakage Current at Application Bus Voltage OFF State Typical values

TABLE 2: SSR Dynamic Response, Pre-Radiation, 25°C, nominal values

Model	Turn On	Turn Off	Rise Time	Rise Time	Fall
Number	Delay	Delay	no Cext	Cext 2000pF	Time
	μSec	μSec	μSec	μSec	µSec
33647	200	50	50	400	50
93647	200	50	50	400	50
83647	200	50	50	400	35
73647	300	50	50	400	25
53647	450	50	50	400	25

TABLE 3: SSR Dynamic Response, Post 100K Radiation, 25°C, nominal values

Model	Turn On	Turn Off	Rise Time	Rise Time	Fall	
Number	Delay	Delay	no Cexi	Cext 2000pF	Time	
	μSec	μSec	μSec	μSec	μSec	
33647	200	100	75	1000	50	
93647	600	100	75	1000	50	
83647	600	100	75	1000	35	
73647	750	100	75	1000	25	
53647	1100	100	75	1000	25	

Specifications subject to change.

# SERIES \*3647

The \*3647 Solid State Relay (SSR) FET switch is driven by a magnetically isolated low level command. The SSR is available with different FET ratings which suit all popular satellite bus voltages. Nominal current and voltage ratings are also shown in Table 1.

Solid State Relays frequently drive loads with capacitive inputs, such as DC-DC converters. In these applications, an uncontrolled rise time can lead to high inrush currents. The MDI \*3647 series has a programmable rise time, allowing user control of inrush current. The output rise time may be externally adjusted by the user from 50 to 400 µSecs via connection of a small capacitor ranging up to 2000pF.

The MDI \*3647 relay FET is mounted on an intrinsic thermal mass, which integrates the effect of the power dissipated during the turn on interval, reducing transient junction temperature rise and stress.

The bias power input requires approximately 30 mA at 5 VDC. This drives a 400 kHz. RF oscillator that supplies drive power to the relay FET. The bias input may also function as a control ON/OFF command input and is available at a nominal 3.3 VDC level.

A dual input logic compatible buffer is also provided so that a low current CMOS signal (less than 1 mA) can drive the input command at either 3.3V or 5V logic levels.



Revised 2015-04-09

## HYBRID SOLID STATE RELAY



**Drain-Source Body Diode**